

MARS T1000

1000FT FULL-DUPLEX INTERCOM SYSTEM
1 PORTABLE BASE STATION WITH 4 BELTPACKS





1000FT Transmission Range



Full-Duplex Wireless Communication



Carrier-Grade Voice Quality



Built-In Battery (Beltpacks)



USB Upgrade




Supports Daisy-Chain Expansion



Supports External Tally



OLED Screen



FEATURES

- 1000ft Working Range
- Carrier-Grade Voice Quality
- Full-Duplex Wireless Communication
- Provide More than 8 Hours of Battery Life
- 1 Base Sation with 4 Beltpacks, Support Cascade Expansion

	Base Station	Beltpack
Power Supply Way	7–36V DC Input;F970 Battery; POE supply(IEEE802.3at)	1600mAh Polymer Lithium Battery
Frequency Response	300Hz to 5KHz	
Signal-to-noise Ration	>50dB	
Distortion	<2%	
Working Range	Under LOS,1000ft working range from Base Station to Beltpack	
Frequency Band	1.9GHz/2.4GHz	
Modulation Mode	GFSK	
Transmit Power	Maximum 24dBm	
Receiver Sensitivity	≤-93dBm	
Bandwidth	1.728MHz	
Power Consumption	<6W	<0.7W
Temperature Range	0 — 40 $^{\circ}$ C (Operation condition); -20 — 60 $^{\circ}$ C (Storage Mode)	
Certification	FCC; CE.	

PACKING LIST





1 00 bligh Coin



TYPE-C Cable







e Station Professional Movingcoil Single-sided Headset

1.9G High-Gain Base Station Antenna

User Manual